### **Connect to Phoenix Contact USA's Printer Resources**

Open web browser and connect to Phoenix Contact's Printer Resources located at <u>http://www.phoenixcontact.com/printers</u>



### **Locate Printer**

Scroll down the page until you see Thermomark Card - 5146464 and click "Driver"



#### **Locate Drivers**

Scroll down the page until you locate the Drivers and Driver Modules section. **Do not click.** 

Firefox PHOENIX CONTACT   Printer Resourc × PHOENIX CONTACT   Thermal transf × +				
♦ ♦ ♠ Attps://www.	phoenixco	ntact.com/online/portal/us?urile=pxc-oc-itemdetail:pid=5146464&librar	y=usen&tab=5	
		Manual de usuario THERMOMARK CARD um_es_thermomark_card_104612_es_02.pdf		
		[pdf, 4 MB] <b>Manual</b> ProdId. 104612: UM PL THERMOMARK CARD Podrecznik uzytkownika THERMOMARK CARD um_pl_thermomark_card_104612_pl_02.pdf	Polish	02
		[pdf, 4 MB] <b>Manual</b> ProdId. 104612: UM SV THERMOMARK CARD Användarhandbok THERMOMARK CARD um_sv_thermomark_card_104612_sv_02.pdf	Swedish	02
	Driv	ers and Driver Modules	Languago	Davision
			Language	Revision
		[Z] Drivers and Driver Modules Device driver Driver_TC_TR_X1_4.6.66.zip	International	4.0.00

### **Download Drivers to Desktop**

Right-Click the Drivers and Driver Modules link and select 'Save Link As...'

NOTE: In Internet Explorer, right-click and choose 'Save Target As ..."



## **Save Driver Files Locally**

Save the .zip anywhere you'd like. It's a temporary file and will be deleted after installation. Be sure to note the save location so you will be able to find the file when the download is completed.

**Recommended:** Locate **Desktop** under Favorites and click **Save.** The .zip file will be located directly on your desktop.

Enter name of file to save to ? 🔀					? 🔀
Save in:	🞯 Desktop		<ul> <li>Image: Image: Image:</li></ul>	• 🖭 👏	
My Recent Documents	Computer My Computer My Network Places	;			
Desktop					
🔗 জ	ows the files, folders, p	rogram shortcuts, and other	items on the d	lesktop.	
My Documents					
My Computer					
<b></b>	File name:	river_TC_TR_X1_4.6.66		<b>~</b>	Save 2
My Network	Save as type: zi	p File		<b>~</b>	Cancel

## **Locate and Extract Files**

Locate Driver\_TC\_TR\_X1\_4.6.66.zip . Right-click and select Extract All...



## **Extraction Wizard**

Click **Next** > to continue.



## **Extraction Wizard**

Select a destination for the extracted files by clicking **Browse**. Then choose a location where you will be able to locate the files.

**Recommended:** Select Desktop to easily find the unzipped folder.

	Extraction Wizard	
n	Select a Destination Files inside the ZIP archive will be extracted to the location you choose.	
str ce cle	Select a folder to extract files to. Files will be extracted to this directory: C:\Documents and Settings\Administrate D B Extracting	Select a destination.
_T	< Back Next >	To view any subfolders, click a plus sign above. Make New Folder OK 3 Cancel

## **Extraction Wizard**

Check the checkbox next to "Show extracted files when complete". Click Finish.



#### **Open Driver Files**

After the files are unpacked, a window will automatically open displaying your newly unzipped folder. Double click the folder to open.

*If a window does not appear*, locate the original .zip file. The unzipped file will be located in the same place.



## **Start Driver Installation**

Within the driver folder, locate **PrnInst.exe.** Double click to start the installation wizard.



# **Begin Driver Installation**

Click **Run >** to begin

Open Fi	Open File - Security Warning 🛛 🛛 🔀		
Do you want to run this file?			
	Name:       PrnInst.exe         Publisher:       Euro Plus d.o.o.         Type:       Application         From:       C:\Documents and Settings\Administrator\My Docu		
🗹 Alwa	Run Cancel		
While files from the Internet can be useful, this file type can potentially harm your computer. Only run software from publishers you trust. What's the risk?			

## **Driver Installation**

Click Next >



## **Selecting the Printer**

Make sure PHOENIX CONTACT is highlighted under Manufacturers. Select **THERMOMARK CARD** from Printers.

Click **Next >** to continue.

1	Selecting the printer			
	Select Printer Please select the manufacturer and printer you want to install.			
	Select the manufacturer and model of your printer. If the driver is in a different folder or your printer came with a driver diskette, click <change location="">. If your printer is not listed, consult your printer documentation for a compatible printer.</change>			
	Manufacturers:       Printers:         PHOENIX CONTACT       CMS-THERMO X1         THERMOMARK CARD       2         THERMOMARK ROLL       THERMOMARK ROLL X1         THERMOMARK W1       THERMOMARK W2         THERMOMARK X1.1       THERMOMARK X1.2			
	Change location			
	Exit Help < Previou 3 Next >			

# **Printer Options**

Select the port\* your printer is connected to.

Click **Finish**.

\*usually USB##

Options	
Printer Options Please select port, prir	iter name and language.
Enter the name for your prin done, select <finish> to ins</finish>	iter. Also, select the port your printer is connected to. When you are tall the printer and add an icon to the Printers folder.
Driver version:	4.6.66.3484
Printer <u>n</u> ame:	THERMOMARK CARD
Available ports:	
TPVM:	1 Add TCP/IP Port
COM1:	
COM2. COM3:	Delete Port
COM4:	
FILE:	
LPT1:	
🔄 I want to use this p	rinter as the Windows default printer.
Select language:	English
	Exit Help C Previous 2 Finish

## **Installation Complete**

The installation will be complete after finishing the previous step. Close all windows and you may now drag **both** Driver\_TC\_TR\_4.6.66 folders to the Recycle Bin.



# Confirmation

To make sure your printer installed correctly, locate **Devices and Printers** on the Start Menu.



## **Devices and Printers**

Your installation was successful if THERMOMARK CARD is listed.



# Setting Up a Printer in CLIP PROJECT

To begin, open the Output Devices Setup window

- 1. File
- 2. Print set<u>up</u>...



# **THERMOMARK CARD - Driver Installation - Windows XP**

#### **Output Devices Setup**

- 1. Select THERMOMARK CARD in Device Configurations
- 2. Click **New**



# Set Up the Printer

- 1. Click on the drop down menu & choose the printer driver
- 2. Click **OK**

🔂 Output devices setup	2	x
Output devices setup Determine, edit, or remove output devices	;, change device configuration.	3
Device configurations		
Plotter	Name: THERMOMARK CARD (1)	
CMS-P1-PLOTTER	Printer parameters Table Material calibration Structure Output layers	
	Printer: THERMOMARK CARD Properties	
CMS-Thermo S1		
THERMOMARK S1	Selected material:	
THERMOMARK CARD	Label preview	
THERMOMARK CARD PLUS		
THERMOMARK W1	Offset X: 0.00 mm	
THERMOMARK X1.1	Offset Y: 0.00 mm	
Bluemark		
	Line thickness:	
	Margin: 1.00	
	Print test page Print speed: Default -	
	Offset for print temperature [%]: 0	
New Duplicate Delete	Apply Heset	
	2 OK Cancel	

# **Installation Complete**

You are now ready to print.

Thank you for using Phoenix Contact's **THERMOMARK CARD** printer!

🖶 THERMOMARK	CARD Printing Preferences	×
Options Adva	nced Setup Dithering	Stocks Printer Memory
Barcode Fonts	International Import/Ex	About INIX
The	mal driver for THERMOMARK ( Version 4.6.66 (Build 3484	CARD printer 4)
	OK Cancel	Apply Help